



WIRELESS

RELAY SWITCH

MODEL NUMBER:

AJ-K102

The Watchman Relay Switch is a low voltage, innovative solution that allows you to integrate Watchman smoke and heat alarms into any existing home security system or isolate power on a particular circuit.

With its advanced technology, the receiver provides a comprehensive and seamless solution for monitoring smoke and fire risks in your home.

The Relay Switch can connect multiple smoke and heat alarms using just one relay switch; this allows for easy connection of all the alarms in the network to the existing home security alarm panel, eliminating the need for multiple receivers.



10YEAR
PRODUCT
WARRANTY



SIMPLE AUTOMATED
INTERCONNECTING



ALL PACKAGING IS
100% RECYCLABLE



PRODUCT & TECHNICAL SPECIFICATIONS:

Product Size:	55 x 40 x 20mm
Weight:	18.7g
Working Voltage:	DC 6-36V
Channels:	1
Standby Current:	< 1 mA
Alarm Current:	< 40 mA
Receiver Sensitivity:	13dBm
Wireless Frequency:	433 MHz
Output Mode:	Switching Signal (Dry Contact)
Working Mode:	Momentary / Toggle / Latching
Max Load of Relay Contact:	7A

FEATURES:

- » RF technology and connects with all Watchman wireless models.
- » Low Voltage
- » Only require one Relay Switch/interface to connect all alarms in a network
- » Interconnectable with up to 21 alarms