



MINI 10 YEAR INTERCONNECTED

HEAT ALARM

MODEL NUMBER:

AJ-770T4

The Watchman Mini 10 Year Interconnected Heat Alarm has been designed to be installed in areas where smoke alarms are not suitable, these areas include; kitchens, garages, and laundries. The alarm will activate once it detects 54°C within the coverage area.

The heat alarm will connect with all other Watchman wireless interconnected alarms and devices - which provides greater protection and early detection throughout the home. When one alarm activates, all other connected alarms will activate. The alarm also contains a quick and automated pairing process and connects with the Watchman Wall Controller for simpler functionality. Heat alarms must not be used as a substitute for smoke alarms.



SIMPLE AUTOMATED
INTERCONNECTING



WALL CONTROLLER
AVAILABLE



ALL PACKAGING IS
100% RECYCLABLE



PRODUCT & TECHNICAL SPECIFICATIONS:

| | |
|----------------------------|------------------|
| Product Size: | 78mm x 57mm |
| Gross Weight: | 0.11kg |
| Sound: | 85dB at 3 meters |
| Humidity: | 95% RH |
| Standby Current: | < 10uA |
| Alarm Current: | < 60mA |
| Optimal Temperature Range: | -10 to +50 |
| RF Frequency: | 433MHz |

FEATURES:

- » Built-in 10 Year 3v lithium battery
- » Automated RF pairing process
- » 9 minute hush
- » Wall Controller available
- » Easy to install
- » 10 year warranty
- » Conforms to BS5446-2:2003
- » NZ Building Code, NZS4514:2021 and RTA compliant